

B & K MODEL 466 PARTS LIST

488-098-9-002B

SCHEMATIC SYMBOL	DESCRIPTION	B & K PART No.
ADAPTERS		
	A, B, C, & D Adapter Assembly	CR-62
	H & J Adapter Assembly	CR-63
	K & L Adapter Assembly	CR-64
MISCELLANEOUS		
ME-1	Case Assembly	523-061-9-001
	Meter	320-028-9-001
	Line Cord	420-001-9-009
PL	Neon Lamp	401-001-9-002

NOTE: Standard value resistors and capacitors are not listed, values may be obtained from schematic diagram.

Minimum charge \$2.00 per invoice. Orders will be shipped C.O.D. unless previous open account arrangements have been made or remittance accompanies order. Advance remittance must cover postage or express.

Specify Serial Number When Ordering Replacement Parts.

SCHEMATIC SYMBOL

DESCRIPTION

B & K PART No.

RESISTORS & CONTROLS

R-1	500KΩ, Trim Pot (HEATER CAL)	008-129-9-001
R-3	10Ω, 5 watt, 10% Wirewound Resistor	006-005-6-100
R-4	1.5KΩ, Trim Pot (COMPRESSION ADJUST)	008-127-9-001
R-7	2.4KΩ, 7 watt, 5% Glass Resistor	003-007-5-242
R-8, R-14	10KΩ, 2 watt, 10% Glass Resistor	003-002-6-103
R-9	500Ω, Trim Pot (EMISSION ADJUST)	008-108-9-001
R-12	2 megΩ, ½ watt, 1% Deposited Carbon Resistor	002-102-3-205
R-13	50KΩ, G ₁ Control	008-135-9-001
R-16 R-17 R-18	100KΩ, G ₂ CUTOFF Control	008-125-9-001
R-19	6KΩ, NORMALIZE Control	008-148-9-001
R-23	3Ω, W.W. HEATER ADJUST Control	009-029-9-001

CAPACITORS

C-1	50μfd, 450 Volt Electrolytic Capacitor	021-003-9-006
C-2	0.22μfd, 200 Volt, 10% Polyester Capacitor	025-028-9-001
C-3, C-4	5μfd, 450 Volt Electrolytic Capacitor	021-006-9-001

TRANSFORMER & SWITCHES

T-1	Power Transformer, 117 Volt Pri. 60Hz	065-059-9-001
S-1	12 Pos. FUNCTION Switch	083-108-9-001
S-2	3 Pos. COLOR GUN Switch	083-094-9-001
S-3	6 Pos. HEATER Switch	083-091-9-001
S-4	REJUVENATE Switch (Push Button)	088-006-9-001

DIODES

D-1	Diode, Silicon 1 ampere, 600 Volt	151-018-9-001
T thru		
D-7		

KNOBS

	Knob, Function Switch	751-005-9-005
	Knob, Clear Spun Insert	751-040-9-001

COMPOSITE

499-020-9-001C