

Model 533A-533DM(SERIES 600)-535

600A-605-605A Tube Testers

Code No. 3200-47

10-1-57

IMPORTANT

RETAIN THIS DATA SHEET

This is a condensed reprint of the roll chart dated October 1 1957, and contains all the older type tubes.

In order to save room on the new chart (Jan. 1, 1958) for new tube data, it was necessary to delete data on older tubes. This older tube data is included here for your use when needed.

NOTE: A Star ★ after P1, P2, P3, and P5 indicates that reading is made on English Scale only.

NOTE: A f in the Bias column indicates Bias should be set at 100 and proper button pressed while Bias dial is rotated until tube strikes.

Table of tube types and specifications including part numbers, ratings, and test procedures. Includes entries like 3A8, 3A8, 3A8, 3AF4A, 3AL5, etc.

Table of tube types and specifications including part numbers, ratings, and test procedures. Includes entries like 0A4, 0Y4, 0Z4, 1A3, 1A4, 1A5, 1A6, etc.

OAY

1L6

5AX4

6B58

6B38	6.3	EV-0603-0	0	78	P1★	Diode No. 1
6B38	6.3	EV-0102-0	0	78	P1★	Diode No. 2
6B35	6.3	EV-3186-0	0	88	P4	5000	Triode No. 1
6B35	6.3	EV-3186-0	0	88	P4	5000	Triode No. 2
6B35	6.3	JR-3702-5	0	58	P4	1260	Triode Sect.
6B35	6.3	JR-0602-5	0	57	P1★	Diode No. 1
6B35	6.3	JR-0502-7	0	57	P1★	Diode No. 2
6B35	6.3	EV-7608-9	15	90	P4	6500	Triode No. 1
6B35	6.3	EV-2103-9	15	90	P4	6500	Triode No. 2
6B35	6.3	JX-0203-0	0	65	P3★	Triode No. 1
Selectors: JX-0503-0 for testers having serial numbers above 135-, 136-, or 138-10000							
6BL7	6.3	JX-2103-0	24	88	P4	5000	Triode No. 1
6BL7	6.3	JX-4506-0	24	88	P4	5000	Triode No. 2
6BN4	6.3	JR-2503-0	19	88	P4	5000	Triode Sect.
6BN6	6.3	JR-2753-6	6	27	700	LIMITER GRID HOLD DOWN P1 AND PRESS P4
6BN6	6.3	JR-6753-2	13	0	500	QUADRATURE GRID HOLD DOWN P1 AND PRESS P4
6BN8	6.3	EV-8709-0	20	73	P4	2000	Triode Sect.
6BN8	6.3	EV-0603-0	0	78	P1★	Diode No. 1
6BN8	6.3	EV-0102-0	0	78	P1★	Diode No. 2
6BQ6	6.3	JR-5047-0	42	87	P4	4500	Cap-P
6BQ7	6.3	EV-7608-0	20	88	P4	5000	Triode No. 1
6BQ7	6.3	EV-2103-0	20	88	P4	5000	Triode No. 2
6BQ7A	6.3	EV-7608-9	13	90	P4	6400	Triode No. 1
6BQ7A	6.3	EV-2103-9	13	90	P4	6400	Triode No. 2
6BR8	6.3	EV-9678-0	7	80	P4	2800	Pent. Sect.
6BR8	6.3	EV-1203-0	12	90	P4	6200	Triode Sect.
6BS8	6.3	EV-7608-9	19	87	P4	4500	Triode No. 1
6BS8	6.3	EV-2103-9	19	87	P4	4500	Triode No. 2
6BT6	6.3	JR-3702-0	12	60	P4	1300	Triode Sect.
6BT6	6.3	JR-3602-0	0	57	P1★	Diode No. 1
6BT6	6.3	JR-3502-0	0	57	P1★	Diode No. 2
6BT8	6.3	EV-8679-0	19	75	P4	2200	Pent. Sect.
6BT8	6.3	EV-0103-0	0	68	P1★	Diode No. 1
6BT8	6.3	EV-0203-0	0	68	P1★	Diode No. 2
6BU6	6.3	JR-3702-0	28	65	P4	1500	Triode Sect.
6BU6	6.3	JR-3602-0	0	50	P1★	Diode No. 1
6BU6	6.3	JR-3502-0	0	50	P1★	Diode No. 2
6BU8	6.3	EV-7821-9	0	15	600	PENT. NO. 1, HOLD DOWN P1 AND PRESS P4
6BU8	6.3	EV-7321-6	0	15	600	PENT. NO. 2, HOLD DOWN P1 AND PRESS P4
6BV8	6.3	EV-2301-0	21	89	P4	5600	Triode Sect.
6BV8	6.3	EV-0907-0	0	78	P1★	Diode No. 1
6BV8	6.3	EV-0608-0	0	78	P1★	Diode No. 2
6BW4	6.3	EV-0709-1	0	20	P3★	Plate No. 1
6BW4	6.3	EV-0109-7	0	20	P3★	Plate No. 2
6BW8	6.3	EV-6987-0	7	80	P4	2800	Pent. Sect.
6BW8	6.3	EV-0302-0	0	77	P1★	Diode No. 1
6BW8	6.3	EV-0102-0	0	77	P1★	Diode No. 2
6BX6	6.3	EV-2781-9	10	86	P4	4200	Triode Sect.
6BX7	6.3	JX-4506-1	33	92	P4	7600	Triode No. 1
6BX7	6.3	JX-2103-5	33	92	P4	7600	Triode No. 2
6BX8	6.3	EV-7608-9	30	82	P4	3200	Triode No. 1
6BX8	6.3	EV-2103-9	30	82	P4	3200	Triode No. 2
6BY5	6.3	JR-0507-0	0	50	P3★	Plate No. 1
6BY5	6.3	JR-0402-0	0	50	P3★	Plate No. 2
6BY6	6.3	JR-3562-7	12	56	P4	1200	Grid No. 1
6BY6	6.3	JR-7562-3	16	0	500	GRID NO. 1, HOLD DOWN P1 AND PRESS P4
6BY8	6.3	EV-1789-2	11	76	P4	2300	Pent. Sect.
6BY8	6.3	EV-0603-0	0	78	P1★	Diode Sect.
6BZ6	6.3	JR-3562-7	13	81	P4	3000	Triode Sect.
6BZ7	6.3	EV-7608-9	15	91	P4	6800	Triode No. 1
6BZ7	6.3	EV-2103-9	15	91	P4	6800	Triode No. 2
6BZ8	6.3	EV-7608-9	20	88	P4	5000	Triode No. 1
6BZ8	6.3	EV-2103-9	20	88	P4	5000	Triode No. 2
6C4	6.3	JR-6307-0	25	75	P4	2200	Triode Sect.
6C5	6.3	JR-5307-0	23	73	P4	2000	Triode Sect.
6C6	6.3	JR-0235-4	20	57	P4	1225	Cap-G
6C7	6.3	JR-0206-0	24	58	P4	1250	Triode Sect. Cap-G
6C7	6.3	JR-0506-0	0	30	P1★	Diode No. 1
6C7	6.3	JR-0406-0	0	30	P1★	Diode No. 2
6C8	6.3	JR-5607-0	20	48	P4	1000	Triode No. 1
6C8	6.3	JR-0304-0	20	48	P4	1000	Triode No. 2
6CA5	6.3	JR-2763-0	20	89	P4	5500	Triode No. 1, Cap-G
6CA7	6.3	JR-5347-2	23	90	P4	6000	Triode Sect.
6CB5	7.5	JR-4023-0	40	92	P4	7000	Cap-P
6CB6	6.3	JR-3562-7	19	75	P4	2200	Triode Sect.
6CD6	6.3	JR-5073-0	35	90	P4	6500	Cap-P
6CE5	6.3	JR-3562-0	11	84	P4	3500	Triode Sect.
6CF6	6.3	JR-3562-7	11	86	P4	4000	Triode Sect.
6CG7	6.3	EV-7608-9	23	79	P4	2600	Triode No. 1
6CG7	6.3	EV-2103-9	23	79	P4	2600	Triode No. 2
6CG8	6.3	EV-9678-0	12	81	P4	3000	Pent. Sect.
6CG8	6.3	EV-1203-0	20	84	P4	3500	Triode Sect.
6CH7	6.3	EV-7608-0	15	91	P4	6800	Triode No. 1
6CH7	6.3	EV-2103-0	15	91	P4	6800	Triode No. 2
6CH8	6.3	EV-7236-0	7	86	P4	4000	Pent. Sect.
6CH8	6.3	EV-8901-0	24	83	P4	3300	Triode Sect.
6CJ6	6.3	EV-2073-1	51	87	P4	4600	Cap-P
6CK6	6.3	EV-2713-6	0	91	P4	7000	Triode Sect.
6CL6	6.3	EV-2631-7	0	90	P4	6000	Triode Sect.
6CL8	6.3	EV-9678-0	10	84	P4	3500	Tetrode Sect.
6CL8	6.3	EV-1203-0	12	89	P4	6000	Triode Sect.
6CM6	6.3	EV-3917-0	13	86	P4	4100	Triode Sect.
6CM7	6.3	EV-7603-0	27	73	P4	2000	Triode No. 1
6CM7	6.3	EV-8109-0	24	87	P4	4400	Triode No. 2
6CM8	6.3	EV-2673-0	11	84	P4	3500	Pent. Sect.
6CM8	6.3	EV-9108-0	12	65	P4	1500	Triode Sect.
6CN7	6.3	EV-7806-0	11	56	P4	1200	Triode Sect.
6CN7	6.3	EV-0203-0	0	77	P1★	Diode No. 1
6CN7	6.3	EV-0103-0	0	77	P1★	Diode No. 2
6CQ8	6.3	EV-2637-0	11	80	P4	2800	Tetrode Sect.
6CQ8	6.3	EV-9108-0	16	88	P4	4800	Triode Sect.
6CR6	6.3	JR-7563-2	12	72	P4	1950	Pent. Sect.
6CR6	6.3	JR-0203-0	0	45	P1★	Diode Sect.
6CS6	6.3	JR-3562-7	0	0	500	GRID NO. 1, HOLD DOWN P1 AND PRESS P4
6CS6	6.3	JR-7562-3	0	31	750	GRID NO. 2, HOLD DOWN P1 AND PRESS P4
6CS7	6.3	EV-7608-0	22	75	P4	2200	Triode No. 1
6CS7	6.3	EV-3109-0	27	87	P4	4500	Triode No. 2
6CU5	6.3	JR-2763-0	0	91	7000	HOLD DOWN P1 AND PRESS P4
6CU6	6.3	JR-5047-0	44	89	P4	5500	Cap-P
6CU8	6.3	EV-7236-1	7	86	P4	4000	Pent. Sect.
6CU8	6.3	EV-8901-0	24	83	P4	3300	Triode Sect.
6CX8	6.3	EV-7986-0	11	87	P4	4700	Pent. Sect.
6CX8	6.3	EV-2301-0	15	84	P4	3600	Triode Sect.
6CY5	6.3	JR-3562-0	12	85	3500	HOLD DOWN P1 AND PRESS P4
6CY7	6.3	EV-7608-0	15	48	P4	1000	Triode No. 1
6CY7	6.3	EV-2109-0	65	85	P4	4000	Triode No. 2
6CZ5	6.3	EV-3917-0	10	87	P4	4500	Triode Sect.

6ST7	6.3	JX-1603-2	20	72	P4	1900	Triode Sect.
6ST7	6.3	JX-0503-6	0	0	P1★	Diode No. 1
6ST7	6.3	JX-0403-6	0	0	P1★	Diode No. 2
6SU7	6.3	JX-4506-1	8	56	P4	1200	Triode No. 1
6SU7	6.3	JX-2103-5	8	56	P4	1200	Triode No. 2
6SV7	6.3	JX-1643-0	6	74	P4	2100	Pent. Sect.
6SV7	6.3	JX-1543-0	0	73	P1★	Diode Sect.
6SZ7	6.3	JX-1603-2	11	56	P4	1200	Triode Sect.
6SZ7	6.3	JX-0503-2	0	15	P1★	Diode No. 1
6SZ7	6.3	JX-0403-2	0	15	P1★	Diode No. 2
6T4	6.3	JR-2305-0	36	88	P4	5000	Triode Sect.
6T5	6.3	JR-5403-0	P4	Eye Open
6T8	6.3	JR-5423-0	P4	Eye Closed
6T7	6.3	JR-0307-0	16	48	P4	1000	Triode Sect. Cap-G
6T7	6.3	JR-0507-0	0	30	P1★	Diode No. 1
6T7	6.3	JR-0407-0	0	30	P1★	Diode No. 2
6T8	6.3	EV-8907-6	11	56	P4	1200	Triode Sect.
6T8	6.3	EV-0607-1	0	77	P1★	Diode No. 1
6T8	6.3	EV-0203-7	0	77	P1★	Diode No. 2
6T8	6.3	EV-0107-8	0	77	P1★	Diode No. 3
6U3	6.3	EV-0903-0	0	60	P3★	Triode Sect.
6U4	6.3	JX-0503-0	0	65	P3★	Triode Sect.
6U5	6.3	JR-5403-0	P4	Eye Open
6U5	6.3	JR-5423-0	P4	Eye Closed
6U6	6.3	JR-5347-0	31	86	P4	4200	Triode Sect.
6U7	6.3	JR-0347-5	15	67	P4	1600	Cap-G
6U8	6.3	EV-2637-0	7	80	P4	2800	Pent. Sect.
6U8	6.3	EV-9108-0	12	90	P4	6200	Triode Sect.
6V3	6.3	EV-0002-0	0	62	P3★	Cap-P Reverse Meter
6V4	6.3	EV-0703-1	0	21	P3★	Plate No. 1
6V4	6.3	EV-0103-7	0	21	P3★	Plate No. 2
6V5	6.3	JX-5340-0	40	86	P4	4100	Triode Sect.
6V6	6.3	JR-5347-2	13	86	P4	4100	Triode Sect.
6V7	6.3	JR-0307-0	42	47	P4	975	Triode Sect. Cap-G
6V7	6.3	JR-0507-0	0	35	P1★	Diode No. 1
6V7	6.3	JR-0407-0	0	35	P1★	Diode No. 2
6V8	6.3	EV-6103-8	13	56	P4	1200	Triode Sect.
6V8	6.3	EV-0903-2	0	40	P1★	Diode No. 1
6V8	6.3	EV-0708-0	0	80	P1★	Diode No. 2
6V8	6.3	EV-0203-8	0	80	P1★	Diode No. 3
6W4	6.3	JX-0503-0	0	60	P3★	Triode Sect.
6W5	6.3	JR-0507-0	0	33	P3★	Plate No. 1
6W5	6.3	JR-0307-0	0	33	P3★	Plate No. 2
6W6	6.3	JR-5347-0	35	87	P4	4500	Triode Sect.
6W7	6.3	JR-0347-5	20	57	P4	1225	Cap-G
6X4	6.3	JR-0607-3	0	20	P3★	Plate No. 1
6X4	6.3	JR-0307-6	0	20	P3★	Plate No. 2
6X5	6.3	JR-0507-2	0	33	P3★	Plate No. 1
6X5	6.3	JR-0307-2	0	33	P3★	Plate No. 2
6X8	6.3	EV-7986-1	12	81	P4	3000	Pent. Sect.
6X8	6.3	EV-2386-1	20	84	P4	3500	Triode Sect.
6Y5	6.3	JR-0504-0	0	65	P3★	Plate No. 1
6Y5	6.3	JR-0304-0	0	65	P3★	Plate No. 2
6Y6	6.3	JR-5347-0	28	88	P4	5000	Triode Sect.
6Y7	6.3	JR					

7R7

7R7	6.3	JR-6257-0	0	78	P4	2500	Pent. Sect.	12Z3	12.6	JR-0203-0	0	50	P3★
7R7	6.3	JR-0407-2	0	0	P1★	Diode No. 1	14A4	12.6	JR-6207-0	23	79	P4	2600
7R7	6.3	JR-0307-2	0	0	P1★	Diode No. 2	14A5	12.6	JR-6237-0	12	81	P4	3000
7S7	6.3	JR-6257-4	15	65	P4	1500	Heptode Sect.	14A7	12.6	JR-6277-4	0	73	P4	2000
7S7	6.3	JR-4357-6	0	60	P4	1300	Triode Sect.	14AF7	12.6	JR-5607-0	23	79	P4	2600
7T7	6.3	JR-6237-4	0	78	P4	2500	14AF7	12.6	JR-4302-0	23	79	P4	2600
7V7	6.3	JR-6237-4	0	80	P4	2750	14B6	12.6	JR-3207-0	0	53	P4	1100
7W7	6.3	JR-6237-5	0	80	P4	2750	14B6	12.6	JR-0607-2	0	36	P1★
7X6	6.3	JR-0607-0	0	55	P3★	Plate No. 1	14B6	12.6	JR-0507-2	0	36	P1★
7X6	6.3	JR-0302-0	0	55	P3★	Plate No. 2	14B8	12.6	JR-6257-4	16	48	P4	1000
7X7	6.3	JR-3204-0	6	42	P4	900	Triode Sect.	14B8	12.6	JR-4357-6	12	0	P4	500
7X7	6.3	JR-0504-0	0	77	P1★	Diode No. 1	14C5	12.6	JR-6237-0	20	81	P4	3000
7X7	6.3	JR-0607-0	0	77	P1★	Diode No. 2	14C7	12.6	JR-6237-4	22	60	P4	1300
7Y4	6.3	JR-0607-0	0	33	P3★	Plate No. 1	14E6	12.6	JR-3207-0	23	72	P4	1900
7Y4	6.3	JR-0307-0	0	33	P3★	Plate No. 2	14E6	12.6	JR-0607-2	0	30	P1★
7Z4	6.3	JR-0607-0	0	24	P3★	Plate No. 1	14E6	12.6	JR-0507-2	0	30	P1★
7Z4	6.3	JR-0307-0	0	24	P3★	Plate No. 2	14E7	12.6	JR-6257-0	22	60	P4	1300
8AU8	7.5	EV-7986-0	9	87	P4	4500	Pent. Sect.	14E7	12.6	JR-0407-2	0	0	P1★
8AU8	7.5	EV-2301-0	15	86	P4	4000	Triode Sect.	14E7	12.6	JR-0307-2	0	0	P1★
8AW8A	7.5	EV-7986-3	10	90	P4	6000	Pent. Sect.	14F7	12.6	JR-5607-3	10	60	P4	1300
8AW8A	7.5	EV-2301-9	15	78	P4	2500	Triode Sect.	14F7	12.6	JR-4302-6	10	60	P4	1300
8BABA	7.5	EV-7986-0	11	88	P4	5000	Pent. Sect.	14F8	12.6	HS-8605-0	7	85	P4	4000
8BABA	7.5	EV-2301-0	30	79	P4	2700	Triode Sect.	14F8	12.6	HS-1304-0	7	85	P4	4000
8BH8	7.5	EV-7986-0	7	88	P4	5000	Pent. Sect.	14H7	12.6	JR-6237-4	0	81	P4	3000
8BH8	7.5	EV-2301-0	27	83	P4	3300	Triode Sect.	14J7	12.6	JR-6257-4	21	35	P4	800
8BN8	7.5	EV-8709-0	20	73	P4	2000	Triode Sect.	14J7	12.6	JR-4357-6	6	48	P4	1000
8BN8	7.5	EV-0603-0	0	78	P1★	Diode No. 1	14N7	12.6	JR-5607-3	23	73	P4	2000
8BN8	7.5	EV-0102-0	0	78	P1★	Diode No. 2	14N7	12.6	JR-4302-6	23	73	P4	2000
8CG7	7.5	EV-7608-9	23	79	P4	2600	Triode No. 1	14Q7	12.6	JR-6237-4	0	35	P4	800
8CG7	7.5	EV-2103-9	23	79	P4	2600	Triode No. 2	14Q7	12.6	JR-4237-6	0	35	P4	800
8CM7	7.5	EV-7603-0	27	73	P4	2000	Triode No. 1	14R7	12.6	JR-6257-0	0	78	P4	2500
8CM7	7.5	EV-8109-0	24	87	P4	4400	Triode No. 2	14R7	12.6	JR-0407-2	0	0	P1★
8CN7	7.5	EV-7806-0	11	56	P4	1200	Triode Sect.	14R7	12.6	JR-0307-2	0	0	P1★
8CN7	7.5	EV-0203-0	0	77	P1★	Diode No. 1	14S7	12.6	JR-6257-4	15	65	P4	1500
8CN7	7.5	EV-0103-0	0	77	P1★	Diode No. 2	14S7	12.6	JR-4357-6	0	60	P4	1300
8CS7	7.5	EV-7608-0	22	75	P4	2200	Triode No. 1	14V7	12.6	JR-6237-4	0	80	P4	2750
8CS7	7.5	EV-3109-0	27	87	P4	4500	Triode No. 2	14W7	12.6	JR-6237-5	0	80	P4	2750
8CY7	7.5	EV-7608-0	15	48	P4	1000	Triode No. 1	14X7	12.6	JR-6237-5	6	42	P4	900
8CY7	7.5	EV-2109-0	65	85	P4	4000	Triode No. 2	14X7	12.6	JR-0504-0	0	77	P1★
8SN7	7.5	JX-4506-0	23	79	P4	2600	Triode No. 1	14X7	12.6	JR-0607-0	0	77	P1★
8SN7	7.5	JX-2103-0	23	79	P4	2600	Triode No. 2	14Y4	12.6	JR-0607-0	0	33	P3★
9AU7	10.0	EV-7608-0	24	75	P4	2200	Triode No. 1	14Y4	12.6	JR-0307-0	0	33	P3★
9AU7	10.0	EV-2103-0	24	75	P4	2200	Triode No. 2	14Z3	12.6	JR-0203-0	0	43	P3★
9CL8	10.0	EV-9678-0	10	84	P4	3500	Tetrode Sect.	15	2.0	JR-0234-0	0	27	700
9CL8	10.0	EV-1203-0	12	89	P4	6000	Triode Sect.	15A6	12.6	EV-2713-6	8	91	P4	7500
9U8	10.0	EV-2637-0	7	80	P4	2800	Pent. Sect.	17AV5	20.0	JR-2573-0	22	89	P4	5500
9U8	10.0	EV-9108-0	12	90	P4	6200	Triode Sect.	17AX4	20.0	JX-0503-0	0	35	P3★
9X8	10.0	EV-7986-1	12	81	P4	3000	Pent. Sect.	17C5	20.0	JR-2763-0	20	90	6000
9X8	10.0	EV-2386-1	20	84	P4	3500	Triode Sect.	17CA5	20.0	JR-2763-0	12	88	P4	5000
10	7.5	JR-3200-0	42	58	P4	1250	17DQ6	20.0	JR-5047-0	25	90	6000
10C8	10.0	EV-8679-0	13	85	P4	4000	Pent. Sect.	17H3	20.0	EV-0301-0	0	45	P3★
10C8	10.0	EV-2103-0	15	84	P4	3500	Triode Sect.	17L6	20.0	JR-5347-0	11	88	5500
10DA7	10.0	EV-7608-0	22	79	P4	2600	Triode No. 1	17R5	20.0	JR-2763-0	20	88	5000
10DA7	10.0	EV-3109-0	55	89	P4	5400	Triode No. 2	18A5	20.0	JR-2573-0	40	88	P4	4800
10DE7	10.0	EV-7608-0	29	73	P4	2000	Triode No. 1	19	2.0	JR-4500-0	23	48	P4	1000
10DE7	10.0	EV-2109-0	55	89	P4	6500	Triode No. 2	19	2.0	JR-3200-0	23	48	P4	1000
11C5	10.0	JR-2763-0	23	87	P4	4500	19AU4	20.0	JX-0503-0	0	60	P3★
12A	5.0	JR-3200-0	44	68	P4	1650	19BG6	20.0	JR-5073-0	12	90	P4	6000
12A4	12.6	EV-8679-0	25	91	P4	7800	19C8	20.0	EV-8907-0	8	58	P4	1250
12A5	12.6	JR-4235-0	35	70	P4	1800	19C8	20.0	EV-8607-0	0	77	P1★
12A6	12.6	JR-5347-2	18	81	P4	3000	19C8	20.0	EV-8203-0	0	77	P1★
12A7	12.6	JR-0236-5	40	47	P4	975	Pent. Sect. Cap-G	19C8	20.0	EV-8107-0	0	77	P1★
12A7	12.6	JR-0504-2	0	40	P3★	Rect. Sect.	19J6	20.0	JR-5207-6	22	78	P4	2500
12A8	12.6	JR-0347-5	11	48	P4	1000	Pent. Sect. Cap-G	19J6	20.0	JR-6307-5	22	78	P4	2500
12A8	12.6	JR-5647-3	11	73	P4	300	Disc. Sect. OK ABOVE 150	19J6	20.0	EV-8907-6	8	56	P4	1200
12AB5	12.6	EV-3917-0	13	86	P4	4100	19T8	20.0	EV-0607-1	0	77	P1★
12AC6	12.6	JR-2657-3	20	15	P1★	OK ABOVE DIODES OK. MAKE NO GAS TEST	19T8	20.0	EV-0203-7	0	77	P1★
12AD6	12.6	JR-7652-3	30	25	P1★	Make no gas test	19T8	20.0	EV-0107-8	0	77	P1★
12AD7	12.6	EV-7608-0	12	58	P4	1250	Triode No. 1	19V8	20.0	EV-6103-8	13	56	P4	1200
12AD7	12.6	EV-2103-0	12	58	P4	1250	Triode No. 2	19V8	20.0	EV-0903-2	0	40	P1★
12AE6	12.6	JR-0702-3	0	0	P1★	TRIODE SECT. OK ABOVE 300 OHM 300 SCALE. MAKE NO GAS TEST	19V8	20.0	EV-0708-6	0	80	P1★
12AE6	12.6	JR-0602-0	0	26	P1★	Diode No. 1	19V8	20.0	EV-0203-8	0	80	P1★
12AE6	12.6	JR-0502-0	0	26	P1★	Diode No. 2	19X3	20.0	EV-0903-0	0	60	P3★
12AE7	12.6	EV-0608-7	0	67	P1★	TRIODE NO. 1	19X8	20.0	EV-7986-1	12	81	P4	3000
12AE7	12.6	EV-0103-2	0	70	P1★	MAKE NO GAS TEST	19X8	20.0	EV-2386-1	20	84	P4	3500
12AF6	12.6	JR-3567-2	26	55	1150	HOLD DOWN PI AND PRESS PA	19Y3	20.0	EV-0903-0	0	60	P3★
12AG6	12.6	JR-7652-3	30	50	P1★	Make no gas test	RIK20A	7.5	JR-3024-0	0	73	P4	2000
12AH7	12.6	JX-6604-3	22	73	P4	2000	Triode No. 1	21A6	20.0	EV-2083-9	42	90	P4	6000
12AH7	12.6	JX-2301-6	22	73	P4	2000	Triode No. 2	22	3.0	JR-0230-0	23	0	500
12AJ6	12.6	JR-0702-3	0	0	P1★	TRIODE SECT. OK ABOVE 300 OHM 300 SCALE. MAKE NO GAS TEST	24A	2.5	JR-0234-0	12	48	P4	1000
12AJ6	12.6	JR-0602-0	0	26	P1★	Diode No. 1	VT25A	7.5	JR-3200-0	30	73	P4	2000
12AJ6	12.6	JR-0502-0	0	26	P1★	Diode No. 2	25A6	25.0	JR-5347-0	25	76	P4	2300
12AL5	12.6	JR-0703-0	0	78	P1★	Diode No. 1	25A7	25.0	JR-5347-6	28	70	P4	1800
12AL5	12.6	JR-0205-0	0	78	P1★	Diode No. 2	25A7	25.0	JR-0602-3	0	50	P3★
12AL8	12.6	EV-0367-2	0	78	P1★	TETRODE SECT. MAKE NO GAS TEST	25AC5	25.0	JR-5307-0	0	65	P4	1600
12AL8	12.6	EV-0109-8	0	0	P1★	TRIODE SECT. OK ABOVE 300 OHM 300 SCALE. MAKE NO GAS TEST	25AV5	25.0	JR-2573-0	50	85	P4	3900
12AQ5	12.6	JR-3562-0	10	86	P4	4100	25AX4	25.0	JX-0503-0	0	35	P3★
12AT6	12.6	JR-3702-0	10	60	P4	1300	Triode Sect.	25B5	25.0	JR-4235-0	0	73	P4	2000
12AT6	12.6	JR-3602-0	0	26	P1★	Diode No. 1	25B6	25.0	JR-5347-0	55	85	P4	4000
12AT6	12.6	JR-3502-0	0	26	P1★	Diode No. 2	25B8	25.0	JR-0342-0	15	70	P4	1800
12AT7	12.6	EV-7608-0	10	85	P4	4000	Triode No. 1	25B8	25.0	JR-7506-0	0	65	P4	1500
12AT7	12.6	EV-2103-0	10	85	P4	4000	Triode No. 2	25BK5	25.0	EV-3186-0	0	88	P4	5000
12AU6	12.6	JR-3567-2	11	76	P4	2300	25BQ6	25.0	JR-5047-0	42	87	P4	4500
12AU7	12.6	EV-7608-0	24	7										

75

Table with multiple columns containing alphanumeric codes, numerical values, and component descriptions. Includes handwritten annotations like '75' and '879'.

5995

879

885

885	2.5	JR-3204-0	# 95	P5★	Strikes at about 68
SD917A	6.3	DU-2105-0	22	65	P4	1500
SN944	6.3	EW-3051-2	15	77	P4	2400
SN946	6.3	CT-0104-0	0	79	P1★
SN946B	6.3	CT-0104-0	0	79	P1★
SN947C	6.3	CU-6135-0	44	87	P4	4500
SN947D	6.3	DW-1572-0	44	87	P4	4500
SN949C	6.3	DW-7105-2	# 65	P3★	Strikes at about 78
950	2.0	JR-3240-0	45	45	P4	950
951	2.0	JR-0230-0	17	35	800
SN953D	6.3	DW-1572-0	15	87	P4	4700
954	6.3	JR-7036-4	23	53	P4	1100
SN954	6.3	ES-0103-0	0	40	P3★
SN954B	6.3	DW-0205-0	0	40	P3★
955	6.3	JR-4306-0	24	72	P4	1900
SN955B	6.3	DW-1708-4	19	81	P4	3000
SN955B	6.3	DW-2508-4	19	81	P4	3000
956	6.3	JR-7036-4	17	65	P4	1500
SN956B	1.1	BS-0000-0	0	0	P3★
957	1.5	JR-4300-0	33	21	P4	650
SN957A	6.3	FT-4102-0	29	75	P4	2200
958	1.5	JR-4300-0	39	56	P4	1200
959	1.5	JR-7030-0	20	15	600
SN972D	6.3	DW-1574-0	19	73	P4	2000
SN973B	6.3	GT-1574-0	19	78	P4	2500
SN976C	6.3	DW-1572-0	44	87	P4	4500
SD993C	6.3	DW-1805-0	25	84	P4	3600
SD995B	6.3	DW-1574-0	19	73	P4	2000
FM-1000	6.3	JR-2453-6	0	31	P4	750
FM-1000	6.3	JR-6453-2	0	42	P4	900
1005	6.3	GX-0305-0	0	96	P5★
1005	6.3	GX-0503-0	0	96	P5★
SN1006	6.3	FT-4102-0	19	62	P4	1400
CK1027	AP-0807-0	0	91	P5★
CK1042	AP-0105-0	0	40	P2★
E1148	6.3	JR-0007-0	0	75	P4	2200
1201	8.3	JS-1304-0	17	81	P4	3000
1203	6.3	JR-0407-0	0	70	P1★
1204	6.3	HS-5314-0	0	67	P4	1600
1229	2.0	JR-0230-0	20	20	640
1230	2.0	JR-3200-0	43	42	P4	900
1231	6.3	JR-6237-4	16	78	P4	2500
1232	6.3	JR-6237-4	20	73	P4	2000
1237	2.5	JR-0300-0	0	77	P3★
1237	2.5	JR-0600-0	0	77	P3★
1247	0.6	EV-0000-0	0	0	P1★
HY1269	12.6	JR-3024-0	0	85	P4	4000
Short on 1 for testers having serial numbers above 135-, 136-, or 138-10000						
1273	6.3	JR-6237-4	22	60	P4	1300
1274	6.3	JR-0507-3	0	33	P3★
1274	6.3	JR-0307-5	0	33	P3★
1280	12.6	JR-6237-4	22	60	P4	1300
1284	12.6	JR-6237-4	23	73	P4	2000
285	25.0	JR-5347-0	33	88	P4	5000
291	2.5	BY-6700-0	27	65	P4	1500
291	2.5	JR-3200-0	27	65	P4	1500
293	1.5	JR-6200-0	28	60	P4	1300
294	1.5	JR-0407-0	0	40	P1★
299	2.5	JR-6230-0	36	74	P4	2100
SR1553D	6.3	JR-2305-0	0	89	P4	5300
1603	6.3	JR-0235-4	20	57	P4	1225
1609	1.1	JR-3240-0	0	27	700
1612	6.3	JR-0347-5	23	21	P4	650
1612	6.3	JR-5347-2	23	21	P4	650
1613	6.3	JR-5347-0	23	73	P4	2000
1614	6.3	JR-5347-2	17	88	P4	5000
1616	4.3	JR-0000-0	0	48	P2★
1619	2.5	JR-5340-7	12	83	P4	3400
1620	6.3	JR-0347-5	20	57	P4	1225
1621	6.3	JR-5347-0	23	73	P4	2000
1622	6.2	JR-5347-0	17	88	P4	5000
1623	6.3	JR-3000-0	0	75	P4	2200
1624	2.5	JR-3020-0	0	82	P4	3200
1625	12.6	JR-4036-0	25	85	P4	3800
1626	12.6	JR-5307-0	46	74	P4	2100
1629	12.6	JR-5407-0	P4
1629	12.6	JR-5437-0	P4
1631	12.6	JR-5347-2	17	88	P4	5000
1632	12.6	JR-5347-0	0	92	8000
1633	25.0	JX-4506-0	23	79	P4	2600
1633	25.0	JX-2103-0	23	79	P4	2600
1634	12.6	JX-4506-2	0	60	P4	1325
1634	12.6	JX-3106-2	0	60	P4	1325
1635	6.3	JR-4307-0	0	35	P4	800
1635	6.3	JR-5607-0	0	35	P4	800
1642	6.3	JR-4506-0	35	62	P4	1375
1643	6.3	JR-0302-0	35	62	P4	1375
1644	12.6	JW-2751-3	0	75	P4	2150
1644	12.6	JW-3451-2	0	75	P4	2150
1651	1.5	DX-0000-0	0	67	P5★
Shorts for testers having serial numbers above 135-, 136-, or 138-10000						
1651	2.0	JR-3200-0	43	42	P4	900
1851	6.3	JR-0347-5	0	88	P4	5000
1852	6.3	JR-4765-3	0	88	P4	5000
1853	6.3	JR-4765-3	0	84	P4	3500
2050	6.3	JR-5307-6	# 95	P5★	Strikes at about 27
2051	6.3	JR-5307-6	# 95	P5★	Strikes at about 27
5516	6.3	JR-5032-0	0	85	P4	4000
Short on 1 for testers having serial numbers above 135-, 136-, or 138-10000						
5517	AP-0807-0	0	48	P2★
5556	4.3	JR-3200-0	26	47	P4	980
5591	6.3	JR-3562-0	0	86	P4	3200
5603	6.3	JR-4760-3	24	85	P4	4000
5608A	2.5	JR-5604-2	0	65	P4	1500
5608A	2.5	JR-3204-6	0	65	P4	1500
5610	6.3	JR-6302-0	27	85	P4	4000
5618	6.3	DX-6218-0	0	81	P4	3000
5633	6.3	EW-3051-2	15	77	P4	2400
5634	6.3	EW-3051-2	17	80	P4	2900
5635	6.3	DW-1708-4	19	81	P4	3000
5635	6.3	DW-2508-4	19	81	P4	3000

6005	6.3	JR-3562-0	10	86	P4	4120
6007	1.1	DV-4210-0	13	0	P1★
6008	0.6	DV-4210-0	13	0	P1★
6012	6.3	JR-3502-7	# 94	P5★	Strikes at about 30
6021	6.3	DW-7805-0	25	78	P4	2500
6021	6.3	DW-2104-0	25	78	P4	2500
6026	6.3	EV-7803-0	25	86	P4	4300
6029	1.1	CU-3100-0	42	73	P4	2000
6052	6.3	DW-0507-4	0	52	P3★
6052	6.3	DW-0102-4	0	52	P3★
6055	25.0	ODW-1805-0	36	73	P4	2000
6072	12.6	EV-7608-0	18	58	P4	1250
6072	12.6	EV-2103-0	18	58	P4	1250
6080	7.5	JX-4506-1	100	83	P4	3400
6080	7.5	JX-2103-5	100	83	P4	3400
6082	25.0	JX-4506-1	100	83	P4	3400
6082	25.0	JX-2103-5	100	83	P4	3400
6084	6.3	EV-9613-8	18	71	P4	1850
6085	12.6	EV-7608-0	18	80	P4	2700
6085	12.6	EV-2103-0	18	80	P4	2700
6086	20.0	EV-2613-9	10	90	P4	6500
6087	5.0	HR-0600-0	0	22	P3★
6087	5.0	HR-0400-0	0	22	P3★
6088	1.1	DV-4120-0	20	0	500
6094	6.3	DV-1428-0	10	86	P4	4100
6101	6.3	JR-5207-6	21	85	P4	4000
6101	6.3	JR-6307-5	21	85	P4	4000
6106	5.0	HR-0600-0	0	35	P3★
6106	5.0	HR-0400-0	0	35	P3★
6110	6.3	DW-0507-4	0	74	P1★
6110	6.3	DW-0102-4	0	74	P1★
6111	6.3	DW-7805-0	26	86	P4	4000
6111	6.3	DW-2104-0	26	86	P4	4000
6112	6.3	DW-7805-0	20	65	P4	1500
6112	6.3	DW-2104-0	20	65	P4	1500
6113	6.3	JX-4506-1	7	58	P4	1250
6113	6.3	JX-2103-5	7	58	P4	1250
6134	6.3	JR-4765-3	0	88	P4	5000
6135	6.3	JR-6307-0	25	75	P4	2200
6136	6.3	JR-3567-2	11	76	P4	2300
6137	6.3	JR-4765-3	12	73	P4	2000
6145	6.3	JR-6237-4	0	89	P4	5500
6146	6.3	JR-5032-7	23	91	P4	7000
6152	6.3	EV-3102-0	28	86	P4	4000
6159	25.0	JR-5032-7	23	91	P4	7000
6169	6.3	DW-1204-0	15	86	P4	4000
6184	6.3	DW-0204-8	0	78	P1★
6184	6.3	DW-0705-8	0	78	P1★
6186	6.3	JR-3562-0	0	85	P4	4000
6197	6.3	EV-2631-7	0	90	P4	6000
6201	12.6	EV-7608-0	10	85	P4	4000
6201	12.6	EV-2103-0	10	85	P4	4000
6202	6.3	JR-0607-3	0	20	P3★
6202	6.3	JR-0307-6	0	20	P3★
6203	6.3	EV-0907-1	0	37	P3★
6203	6.3	EV-0107-9	0	37	P3★
6205	6.3	DW-1572-4	19	78	P4	2500
6211	12.6	EV-7608-2	24	84	P4	3600
6211	12.6	EV-2103-7	24	84	P4	3600
6216	6.3	EV-2173-0	20	92	P4	9000
6247	6.3	DW-2805-0	11	73	P4	2000
6265	6.3	JR-3562-7	12	73	P4	2000
6293	6.3	JR-5032-0	24	90	P4	6500
6350	12.6	EV-8607-3	26	87	P4	4600
6350	12.6	EV-3102-8	26	87	P4	4600
6355	6.3	FR-3827-0	0	P4
6355	6.3	FR-8327-0	0	P4
6386	6.3	KR-7608-5	24	86	P4	4000
6386	6.3	KR-3402-5	24	86	P4	4000
6397	2.5	HR-8360-0	33	72	P4	1950
6417	12.6	EV-9167-3	0	88	P4	5000
6463	12.6	EV-8607-1	25	88	P4	5200
6463	12.6	EV-3102-6	25	88	P4	5200
6485	6.3	JR-3562-2	0	88	P4	5000
6660	6.3	JR-3567-2	0	79	P4	2700
6661	6.3	JR-3562-7	12	73	P4	2000
6662	6.3	JR-3562-7	0	78	P4	2500
6663	6.3	JR-0703-6	0	78	P1★
6663	6.3	JR-0205-6	0	78	P1★
6669	6.3	JR-3562-0	10	86	P4	4100
6677	6.3	EV-2631-7	0	90	P4	6000
6678	6.3	EV-2631-7	7	80	P4	2800
6678	6.3	EV-9108-0	12	90	P4	6200
6679	12.6	EV-7608-0	10			