

SCHEMATIC SYMBOL

DESCRIPTION

B & K-PRECISION PART NO.

MISCELLANEOUS

F1	Fuse 3/10 A, 250 V, 3 AG Slow-Blow	190-004-9-001
PL1	Neon Bulb, NE-2 with 7" Leads	401-016-9-001
T1	Power and Filament Transformer (120 V)	065-105-9-001
	Power and Filament Transformer (120/240 V)	065-105-9-002
M1	Meter	320-061-9-001
	Line Cord (U.S. Version)	420-034-9-009
	Line Cord (CSA Version)	420-013-9-001
	Line Cord (Export Version)	420-010-9-001
	Case Assembly	523-490-9-001
	Knob, Function	751-005-9-008
	Knob, Small	751-112-9-001
	Knob, Gun Selector and Htr. Range	751-115-9-001
	Knob, Pushbutton Black	384-016-9-006
	Lens Cap, Red	750-003-9-001
	Tube Chart	497-019-0-000
	Instruction Manual	480-159-9-001
	Guarantee, CRT, 20 Per Pad	483-174-9-001
	Output Cable Assembly	427-013-9-001
	Rubber Foot	381-002-9-001
	Vinyl Divider Flap	758-021-9-001
	Hinge Wire	763-027-9-001
	Adapter Storage Assembly	523-103-9-001

PARTS ORDERING INFORMATION

There is a minimum charge for each invoice. Orders will be shipped C.O.D. unless previous open account arrangements have been made or remittance accompanies order. Advance remittance must cover handling, postage, or express charges. Specify model and serial number when ordering replacement parts.

ORDER REPLACEMENT PARTS FROM:

B & K-Precision, Dynascan Corporation
 Factory Service Operations
 6460 West Cortland Street
 Chicago, Illinois 60635
 Tel (312) 889-8870
 Telex: 25-3475



BK PRECISION
 DYNASCAN CORPORATION

6460 W. Cortland St. • Chicago, IL 60635
 312-889-8870

SERVICING INFORMATION



MODEL 470

CRT TESTER/REJUVENATOR

PARTS LIST
 488-144-9-002J

SCHEMATIC SYMBOL

DESCRIPTION

B & K-PRECISION PART NO.

ELECTROLYTIC CAPACITORS

C1	5 µF, 250 VDC	021-018-9-001
C2, 3	50 µF, 450 VDC	021-056-9-001

DIODES

D2	Germanium Diode, 1N67	150-008-9-001
D1, 3-9	Rectifier, 600 PIV, 1 A	151-050-9-001

RESISTORS AND CONTROLS

Standard value resistors are not listed. Values may be obtained from schematic diagram.

R1	3 Ω, ±10% Linear, 12-1/2 W, Wire Wound Pot	009-038-9-001
R3	50 kΩ, ±10% Linear, 1/2 W, Carbon Pot	008-135-9-001
R6	1 MΩ ±1%, 1/2 W, Metal Film Resistor	011-061-9-001
R7	50 kΩ ±30%, Horizontal Mount Linear Trimmer Pot	008-224-9-001
R9	49.9 Ω, ±1%, 1/4 W, Metal Film Resistor	011-218-9-001
R10	1 kΩ, ±30%, Logarithmic Taper Carbon Pot	008-213-9-001
R11	0.99 Ω, ±1%, 1/2 W, W.W. Resistor	004-115-9-001
R13, R14	2.5 kΩ, ±10%, 7 W, W.W. Resistor	014-007-6-252
R15	4.7 Ω, ±10%, 1/2 W, W.W. Resistor	006-102-9-479
R17 - 19	200 kΩ, ±10%, 2 W, Pot	008-819-9-001

SWITCHES

S1	11-Position Rotary Switch (Function)	083-168-9-001
S2	3-Position Rotary Switch (Gun Selector)	083-170-9-001
S3	6-Position Rotary Switch (Htr. Range)	083-091-9-001
S4	Pushbutton Switch 3PDT Momentary	088-026-9-001