



SPECIFICATIONS

1. Antenna Coupler

- Frequency range 8 amateur bands from 3.5 to 29.7 MHz
- Input impedance 50Ω
- Output impedance 20 to 300Ω, unbalanced.
- Through power 150W max. (3.5 MHz band, 120W)
- Insertion loss Less than 0.5dB at optimum match.

2. SWR Meter

- Frequency range 3.5 to 29.7MHz
- Max. power 150W
- Measurable range 1.0:1 to 10:1
- Min. power required 2W

3. General

- INPUT Connector UHF type (50Ω)
- ANT Connector UHF type (50Ω)
- GND Wing nut and STUD.
- Dimensions H. 60mm (2-3/8")
W. 152mm (6")
D. 159mm (6-1/4")
- Weight 1.6kg (3.5 lbs) approx.

NOTE: The circuit and ratings may change without notice due to developments in technology.

SCHEMATHEEK
Beh. T. Hultermans
Postbus 4228
5804 EE Eindhoven

