



**KENWOOD**

# SERVICE MANUAL

Downloaded by  
RadioAmateur.EU

## HS-5



**Headphones**

# SPECIFICATIONS

Impedance.....	8 ohms
Maximum input.....	200 mW (1000 Hz)
Frequency response.....	150 ~ 4000 Hz (-6 dB)
Connecting cord.....	2m (with plug)
Weight.....	Approx. 350g

\* Specifications are subject to change without notice for improvement.

# GENERAL

This headphone is designed exclusively for use with communication system. It provides many hours of comfortable listening and clear sound. This monaural type headphone has a specific frequency response for excellent tonal quality.

# FEATURES

- **Ideal tonal quality for communication use**  
Mylar film cones are used to ensure clear sound and many hours of fatigueless listening.
- **Open air system for comfortable listening and lightweight design**  
Provides natural sound and eliminates uncomfortable pressure feeling. Specially designed for communication use to ensure excellent sound dispersion.
- **Ear-pads can be replaced according to listening conditions**  
The ear-pads fitted to the headphone are suited for most of listening conditions. However, they can be replaced with the supplied pressure-fit type ear-pads, if you wish to increase the volume level or when you are using the headphone at midnight or in a noisy room.
- **New design that perfectly matches Kenwood's communication equipment**

# PARTS LIST

☆: new parts

Ref. No.	Parts No.	Description	Remarks
1	T97-1001-08	Driver unit	☆
2	T97-1002-08	Protector ass'y (L)	☆
3	T97-1003-08	Protector ass'y (R)	☆
		Protector	
		Ornament ring	
		Driver holding ring	
		Cover holding plate spring × 2	
		Tapping screw (3 × 6) × 2	
		Slider	
		Case holding frame	
		Pivot (A) × 2	
		Pivot (B)	
		Polyethylene slider washer	
		Plain washer	
		E ring × 2	
4	T97-1004-08	Sound shielding ring	☆
5	T97-1005-08	Back cover ass'y	☆
		Ornament plate	
		Back cover	
6	T97-1006-08	Patch cord retaining ring × 2	☆
7	T97-1007-98	Cord retaining ring	☆
8	T97-1008-08	Ear-pad ass'y × 2	☆
		Ear-pad	
		Retaining plate	
9	T97-1009-08	Pressure-fit type ear-pad ass'y × 2	☆
		Pressure-fit type ear-pad	
		Retaining plate	
10	T97-1010-08	Cord ass'y	☆
		2P plug cord	
		Vinyl tube	
		Cord binder	
11	T97-1012-08	Slider case ass'y × 2	☆
		Slider case	
		Slider rear case	
		Slider spring	
		Felt	
		Tapping screw (3 × 10) × 2	
		Model nameplates	
12	T97-1013-08	Head pad × 2	☆
13	T97-1014-08	Head band × 2	☆
14	T97-1015-08	Patch cord	☆
—	B50-2527-00	Instruction manual	
—	T97-1016-08	Gift box	
—	T97-1018-08	Vinyl bag	

# EXPLODED VIEW

All parts are assembled as units. Do not attempt to disassemble unnecessarily, as they are hard to be reassembled.

Downloaded by  
RadioAmateur.EU

