



B&K 440 Cathode Ray Tube Tester

- M-1 SWITCH POSITION**
1. CONT. SHORT
 2. EMISSION
 3. CUT-OFF
 4. REMOVE SHORTS
 5. DYN. LOW
 6. DYN. MED.
 7. DYN. HIGH

LAST "R" No 12
LAST "C" No 2

ALL RESISTORS $\frac{1}{2}$ WATT UNLESS OTHERWISE INDICATED
MODEL NO. 440 SCHEMATIC

B & K MFG. CO., INC. • CHICAGO, ILLINOIS

B & K Model 440 Parts and Price List

SCHEMATIC SYMBOL	DESCRIPTION	B & K PART No.	DEALER'S NET
C-1	5 MFD 250 V Electrolytic Cap.	CL-5-250	\$.73
C-2	0.1 MFD 1000 V Tubular Capacitor	CP-A1-1000	.38
M-1	Function Switch	S-40	2.10
M-2	Heater Switch	S-7	1.38
M-3	High-Low Emission Switch.....	S-22	.15
M-4	Red-Green-Blue Gun Selector Switch.....	S-3	.35
M-5	Dyna Intensifier Switch, 1 Pole 1 Pos. Normally Open (Red Button)	S-17	1.08
M-6	Life Test Switch, 1 Pole, 1 Pos. Normally Closed (Black Button)	S-19	.99
M-7	"H" Indicator. Ne-48 Neon Lamp	PL-7	.70
M-8	"G1" Indicator. NE-48 Neon Lamp	PL-7	.70
M-9	"G2" Indicator. NE-48 Neon Lamp	PL-7	.70
M-10	Meter	ME-7	12.60
R-1	220 K Ohm ½ W 10% Resistor.....	RC-224-A-10	.09
R-2	4.7 K Ohm 1 W 10% Resistor.....	RC-472-B-10	.09
R-3	150 K Ohm ½ W 10% Resistor.....	RC-154-A-10	.09
R-4	500K Ohm Cut off Bias Control with On-Off Switch.....	P-45	.91
R-5	560 K Ohm ½ W 10% Resistor.....	RC-564-A-10	.09
R-6	10 K 1 W 10% Resistor.....	RC-103-B-10	.09
R-7	1 Megohm ½ W 10% Resistor.....	RC-105-A-10	.09
R-8	56 K Ohm 7 W 10% Glass Resistor.....	RG-563-7-10	.45
R-9	220 K Ohm ½ W 10% Resistor.....	RC-224-A-10	.09
R-10	10 K Ohm ½ W 10% Resistor.....	RC-103-A-10	.09
R-11	47 K Ohm ½ W 10% Resistor.....	RC-473-A-10	.09
R-12	47 K Ohm ½ W 10% Resistor.....	RC-473-A-10	.09
T-1	Transformer, Heater	TF-2	5.76
T-2	Transformer, High Voltage.....	TP-12	3.75
V-1	6X4 Tube.....	V-6X4	.92

MISCELLANEOUS PARTS

Test Socket "A".....	ASM-34	1.95
Test Socket "B".....	ASM-35	1.95
Test Socket "C".....	ASM-36	1.95
Duo-Decal Socket and Cable Assembly, Regular ...	G-28	1.53
Neo-Diheptal Socket and Cable Assembly, Color ...	G-29	2.91
AC Line Cord.....	W-14	.33
Knob	K-7	.15
Carrying Case	LG-4	7.50
Lens Cap and Bushing.....	LS-8	.69
Neon Indicator Socket Assembly.....	LS-10	1.20
7 Pin Socket.....	G-7PF	.12
Carton and Fillers.....	PKG-32	.67
Instruction Manual.....	PM-41	.18

(Prices subject to change without notice.)