

## Hallicrafters, Inc.

**Model: S-21**

**Chassis:**

**Year: Pre 1948**

**Power:**

**Circuit:**

**IF:**

**Tubes:**

**Bands:**

**Resources**

**Riders Volume 15 - HALLICRAFTERS 15-58**

MODEL Skyrider 5-10  
S-21

THE HALLICRAFTERS CO.

NO.	CAPACITY	TYPE	VOLTAGE	PARTS NO.
08	.002 mfd.	mica		40-013
9	.05 "		200	41-004
10	.05 "		400	41-005
11	Tuning Condenser in I.F. Transformer			
12	" "	" "		
13	.01 mfd.		400	41-001
14	.01 "		200	41-000
15	.05 "		400	41-005
16	.01 "		400	41-001
17	Tuning Condenser in I.F. Transformer			
18	" "	" "		
19	.01 mfd.		400	41-001
20	.25 "		400	
21	.01 "		200	41-000
22	.01 "		400	41-001
23	.00025 "	mica		40-024
24	Pad			
25	.00025 "	air		48-021
26	.01 "		400	41-004
27	Tuning Condenser in I.F. Transformer			
28	" "	" "		
29	.02 mfd.		400	41-002
30	.0001 "	mica		40-003
31	.02 "		400	41-002
32	.0001 "	mica		40-003
33	.05 "		200	41-004
34	.1 "		200	41-006
35	.0001 "	mica		40-003
36	.01 "		400	41-001
37	.01 "		600	45-002
38	.01 "		600	45-002
39	20. "		25	42-025
40	.05 "		400	41-005
41	.002 "	mica		40-013
42	.0001 "	"		40-003
43	.400 mmfd.	Pad		44-037
44	10. mfd.		450	
45	10. "		450	42-024
46	10. "		450	
47	.01 "		600	45-002
81	A.V.C. - B.F.O. On-Off Switch			
82	Automatic Noise Limiter and I.F. Expander Switch			
83	A.C. On-Off Switch on Tone Control			
84	Stand By SPST			
85	Meter Switch on R.F. Gain Control			

NO.	OHMS	WATTAGE	PARTS NO.
R1	160	1/3	22-011
2	100,000	1/3	20-093
3	1,000	1/3	20-033
4	600	1/3	22-125
5	30,000	1	22-075
6	2,500	1/3	22-044
7	100,000	1/3	20-093
8	500	1/3	22-026
9	10,000	R.F. Gain Control	25-029
10	2,500	1/3	22-044
11	100,000	1/3	20-093
12	500	1/3	24-040
13	50,000	1/3	20-084
14	50,000	1/2	22-082
15	1,000	1/3	20-033
16	20,000	1/3	22-071
17	1,000,000	1/3	20-018
18	500,000	Tone Control	25-018
19	100,000	1/3	20-093
20	100,000	1/3	20-093
21	250,000	1/3	20-099
22	300	1/3	20-021
23	500,000	A.F. Gain Control	25-031
24	25,000	1	20-073
25	20,000	1	20-070
26	150	1/3	22-011
27	100,000	1/3	20-093
28	500	1/3	24-040
29	500,000	1/3	22-101
30	10,000	1	20-061
31	50,000	1/3	20-084
32	5,000	2	

CONDENSER PARTS LIST - SKYRIDER 5-10 Model S21

NO.	CAPACITY	TYPE	VOLTAGE	PARTS NO.
C1	80 mmfd per section	main tuning		48-033
2		gang		
3		mica		
4	.005 mfd.	"		40-013
5	.002 "	"		41-001
6	.01 "	"	400	
7	.01 "	"	600	45-002